



# Winding OhmMeter RMO50T

- Lightweight – 13 kg
- Test current 5 mA – 50 A DC
- Measuring range 0,1  $\mu\Omega$  - 2 k $\Omega$
- Two voltage sense channels
- Extremely quick measurement
- Automatic discharge circuit
- Built-in Tap Changer Control Unit



## High DC current resistance meter for transformers/motors

### Description

The ohmmeter RMO50T is designed for resistance measurement of inductive test objects. RMO50T generates true, filtered DC current. Both injection of current and discharge of energy from the inductance are automatically regulated.

RMO50T injects current with a voltage as high as 60V. This ensures that the duration of test is as short as possible, and that the desired test current is reached as soon as possible. Two independent channels enable testing of two series windings, or primary and secondary windings. There is enough memory within RMO50T instrument to store 500 measurements. All measurements are time and date stamped.

The set is equipped with thermal and overcurrent protection. The RMO50T has very high ability to cancel electrostatic and electromagnetic interference in HV electric fields. It is achieved by very efficient filtration. The filtration is made utilizing appropriate hardware and software.

### On Load Tap Changers

The RMO50T can be used to measure winding resistance of individual taps of a power transformer's tap changer. It can also check whether the on-load tap changer (OLTC) switches without an interruption. The moment a tap position is changed from one tap to another, the device detects a sudden, very short drop of the current. A properly working tap changer differs from a malfunctioning one. This is obvious from an interruption during the change, and by the magnitude of the ripple. An interruption will result in much higher ripple value than a properly functioning tap changer that operates without interruption.

The Tap Changer Control Unit allows the operator to control the Tap Changer operation box from the RMO50T position.

### RMOWin-T

Using RMOWin-T software, tests could be performed from a PC, and results can be obtained directly at a PC. Utilizing RMOWin-T software, results can be arranged in an Excel spreadsheet, which can be shown later as a diagram and printed for a report. Using a PC with RMO-T device it is possible to conclude about tap changer conditions analyzing a graph which represents dynamic resistance during tap changes.




## Typical application

Typical application of RMO50T is measuring the resistance of:

- ✓ Power transformers
- ✓ On-Load Tap Changers
- ✓ Generators and electrical motors
- ✓ High-current busbar joints
- ✓ Cable splices




## Standard accessories

- ✓ RMOWin-T PC software
- ✓ Current cables 2x10m 10mm<sup>2</sup>
- ✓ Sense cables 2x2x10m 2,5mm<sup>2</sup>
- ✓ Current connection cable 1x5m 10mm<sup>2</sup>
- ✓ Built-in Tap Changer Control Unit
- ✓ Tap Changer Control cable set 5m
- ✓ Mains power cable
- ✓ Ground (PE) cable
- ✓ Cable bag

		
Voltage sense cables	Current cables	Current connection cable



## Optional accessories

- ✓ Built-in thermal printer
- ✓ Test shunt 75A/150mV
- ✓ Current cables 2x15m 10mm<sup>2</sup>
- ✓ Sense cables 2x2x 15m 2,5mm<sup>2</sup>

		
RMO50T	Shunt	Cable bag


## Connecting a Test Object to RMO40T

The RMO40T should be turned off, connection between RMO40T and the test object is such that the measuring cables from the "Voltage Sense" sockets are attached as close as possible to the measured resistance, while they are connected between the current feeding cables. That way, resistance of cables and clamps is almost completely excluded from the resistance measured. The figure to the right shows simultaneous testing of both windings (high and low) on a single-phase transformer. In such a way, it is possible to speed up the measurement when two channels are used to test both windings of the transformer.



Testing of a Delta-delta winding resistance is usually a very time consuming procedure. This is because the two windings represent two closed loop inductors. When energy is brought into the inductors, this energy (in the form of D.C. current) continually circulates within each winding. To test this configuration quickly, both high and low sides should be connected in series with the current source of a Transformer Ohmmeter. By having these two windings in opposing polarity, the internal circulating currents settle very quickly to obtain a balance, and discharge with the same speed. Even if only one side of the transformer needs to be tested, connecting both high and low

Using RMO40T's Tap Changer menu, the power transformer winding resistance of individual tap positions can be measured. Also, you can check whether the on-load tap changer switches without an interruption. The RMO40T current output injects a constant current into a power transformer. This current and voltage value is measured, and the winding resistance is calculated.



## Technical data

### 1 - Mains Power Supply

- Connection according to IEC/EN60320-1; UL498, CSA 22.2
- Voltage single phase 110 – 240 V AC, + 10 % - -15 %
- Frequency 50 / 60 Hz

### 2 - Output data

- Test current 5 mA DC – 50 A DC
- Measuring range / Resolution
  - 0,1  $\mu\Omega$  - 999,9  $\mu\Omega$  0,1  $\mu\Omega$
  - 1,000 m $\Omega$  - 9,999 m $\Omega$  1  $\mu\Omega$
  - 10,00 m $\Omega$  - 99,99 m $\Omega$  10  $\mu\Omega$
  - 100,0 m $\Omega$  - 999,9 m $\Omega$  0,1 m $\Omega$
  - 1,000  $\Omega$  - 99,99  $\Omega$  10 m $\Omega$
  - 100,0  $\Omega$  - 999,9  $\Omega$  0,1  $\Omega$
  - 1000  $\Omega$  - 2000  $\Omega$  1  $\Omega$
- Typical accuracy  $\pm(0,2\% \text{ rdg} + 0,2\% \text{ FS})$

### 3 – Environmental conditions

- Operating temperature  $-10^{\circ}\text{C} - +50^{\circ}\text{C} / 14^{\circ}\text{F} - +122^{\circ}\text{F}$
- Storage and transportation  $-25^{\circ}\text{C} - +70^{\circ}\text{C} / -13^{\circ}\text{F} - +158^{\circ}\text{F}$
- Humidity 5 % - 95 % relative humidity, non condensing

### 4 - Dimensions and Weight

- Dimensions 502 mm x 190 mm x 395 mm  
19,75 in x 7,48 in x 15,53 in  
(W x H x D)
- Weight 13 kg/28,6 lb

### 5– Safety Standards

- European standards EN 61010-1
- International standards IEC 61010-1

### 6 – Electromagnetic Compatibility (EMC)

- CE conformity EMC standard 89/336/EEC
- Emission EN 50081-2, EN 61000-3-2/3
- Interference Immunity EN 50082-2

Specifications are subject to change without notice.



**IBEKO POWER AB**